



Troubleshooting

If you are having a problem with the controller, check the following symptoms, possible causes and remedies. If the problem can not be resolved or you would like assistance with any Toro irrigation product, call 1-800-664-4740 or 1-951-688-9221 (outside U.S.) Monday through Friday, 7:30 a.m – 4:00 p.m. (Pacific Standard Time).

Symptom	Possible Cause	Remedy
The display is blank and the controller does not operate.	Main power is disconnected.	Check the transformer connections (indoor model) or circuit breaker at service panel (outdoor model).
Watering programs start at unscheduled times.	Watering programs have overlapping start times (stacked).	Reduce station times. Change/remove program start times. (See p. 27).
A station does not turn on.	Faulty wire connection at station module. Shorted valve wire connection or faulty solenoid. Electronic Fuse has disabled station operation.	Remove wire from station module. Strip back enough insulation to see 1/8" (3mm) of bare wire when fully inserted. Repair wire connections. Inspect solenoid and repair or replace as necessary.
A station does not turn off.	No station time entered. Valve problem generally caused by a bonnet leak or corroded solenoid.	Enter a station time (See p. 28). Inspect valve bonnet seal and/or solenoid. Replace as needed.
Program starts again after completion of a watering cycle.	Season Adjust setting greater than 100%. Watering programs have overlapping start times (stacked).	Review Season Adjust factor and reset to 100%. (See p. 34) Reduce station times. Change/remove program start times. (See p. 27).

